

HUNTRON PROTRACK SCANNER I

OPERATION MANUAL

April 1996
P/N 21-1251
Rev. 4, 11/05

Copyright © 2005 Huntron, Inc. All rights reserved.

Huntron, Tracker, ProTrack, Sig Assist and Huntron Access are registered trademarks of Huntron, Inc. All other names are trademarks or registered trademarks of their respective companies.

This document may not be copied in whole or in part, or otherwise reproduced except as specifically permitted under U.S. copyright law, without the prior written consent of Huntron, Inc., 15720 Main Street, Suite#100, Mill Creek, WA, 98012, USA.

HUNTRON INSTRUMENTS, INC.

LIMITED WARRANTY

Huntron, Inc. believes in the quality of its products. Accordingly, Huntron provides the following non-transferable warranties for the benefit of the original end-use purchaser of the Huntron[®] ProTrack Scanner I instrument.

Huntron warrants that the Huntron ProTrack Scanner I hardware shall be free from defects in material and workmanship for one (1) year from the date of purchase.

This warranty shall only apply to products in ordinary use. Huntron shall have no obligation under this warranty with respect to damage caused by accident, transportation, neglect, misuse, unauthorized alterations or repair, improper installation, or operating conditions.

Products purchased in the United States are to be returned to Huntron, Inc. at its factory, transportation prepaid. Products purchased outside the United States are to be returned to the source of purchase for warranty repair.

Written notice of, and an explanation of the circumstances of, any defect believed to be covered by this agreement shall be provided promptly to Huntron by the customer following discovery of the defect. In satisfaction of its warranty liability, Huntron agrees to take reasonable and prompt action to correct the defect, either by repair or replacement, at its option.

ABOUT THIS MANUAL

This manual covers the general operation of your instrument.

CONTACTING HUNTRON

To obtain information about service, accessories and other products, contact:

Huntron, Inc.
15720 Main Street, Suite #100
Mill Creek, WA 98012
USA

In North America, call 800-426-9265 or 425-743-3171.

Huntron is also accessible by:

- ◆ FAX: 425-743-1360
- ◆ Internet E-mail: huntron@huntron.com
- ◆ Internet Home Page: <http://www.huntron.com>

TABLE OF CONTENTS

Section 1	INTRODUCTION AND SPECIFICATIONS	
1-1	INTRODUCTION.....	1-1
1-2	SPECIFICATIONS	1-2
1-3	SAFETY CONSIDERATIONS	1-3
1-4	WEEE AND ROHS STATUS	1-5
Section 2	OPERATING INSTRUCTIONS	
2-1	INTRODUCTION.....	2-1
2-2	UNPACKING YOUR INSTRUMENT	2-1
2-3	PHYSICAL FEATURES	2-2
2-4	SETUP	2-3
2-5	TYPICAL APPLICATIONS.....	2-4
2-6	EXTERNAL CLEANING	2-5
2-7	STORAGE INSTRUCTIONS	2-5

LIST OF ILLUSTRATIONS

Figure	Description	Page
1-1	Huntron ProTrack Scanner I and ProTrack I	1-1
2-1	External Features	2-2
2-5	Typical Applications	2-4

LIST OF TABLES

Table	Description	Page
1-1	ProTrack Scanner I Specifications	1-2
2-1	Controls and Connectors.....	2-3

Notes:

SECTION 1

INTRODUCTION AND SPECIFICATIONS

1-1. INTRODUCTION

The Huntron ProTrack Scanner I, shown in Figure 1-1, has been designed as a compatible interface for the Huntron ProTrack I Model 20. Together, they create an effective test system for component troubleshooting. The ProTrack Scanner I allow faster comparison testing of components by the use of ZIF (zero insertion force) sockets for out of circuit components and by the use of DIP (dual inline package) clip cables for in-circuit ICs (integrated circuits).




Figure 1-1. Huntron ProTrack Scanner I and ProTrack I.

1-2. SPECIFICATIONS

The specifications for the ProTrack Scanner I are listed in Table 1-1.

Table 1-1. ProTrack Scanner I Specifications.

ELECTRICAL

Interconnections:

Channels

Number.....2

Pins

Test.....64 per channel

Common.....64 per channel

Connectors

IDC64 pins each channel

ZIF40 pins each channel

Input Power Requirements

Voltage5VDC

Current.....4A (max)

Scanner I Power Supply (external unit)

Line Voltage.....100VAC to 240VAC

Frequency.....50/60 Hz

Input Current.....0.7A

Output Voltage.....5VDC

Output Current.....4A (max)

GENERAL

Size.....12" W x 3" H x 19.5" D
(30.5cm W x 7.6cm H x 49.5cm D)

Weight5lbs. 8oz., (2.5kg)

ENVIRONMENTAL

Indoor Use

Altitude.....<2000m (<6560')

Temperature

Operating0°C to +40°C (32°F to 104°F)

Storage-20°C to +60°C (-4°F to 140°F)

Relative Humidity.....0 to 80% from 0°C to 31°C (32°F to 88°F)
Maximum R.H. decreases linearly to 50%
at 40°C

SAFETY.....According to IEC 1010-1

OverVoltage Category

Ext. Power SupplyCAT II

Scanner ICAT I

Pollution Degree2

1-3. SAFETY CONSIDERATIONS

Safety Terms and Symbols

Terms in this Manual. These terms may appear in this manual:




Warning statements identify conditions or practices that could result in injury or loss of life.




Caution statements identify conditions or practices that could result in damage to this product or other property.

Symbols on the Instrument. These symbols may appear on the instrument:

 Earth Terminal

 Protective Ground
(Earth) Terminal

 **CAUTION**
Refer to Manual

 Fuse

Review the following safety precautions to avoid injury and prevent damage to this instrument. The user shall be made aware that, if the instrument is used in a manner not specified by the manufacturer, the protection provided by the instrument may be impaired.

Only qualified personnel should perform service procedures.

TO AVOID FIRE OR PERSONAL INJURY

Use Proper Power Cord. Use only the power cord certified for the country of use.

 **WARNING**

The detachable power cord is the means with which to disconnect the instrument from the mains voltage supply. Therefore do not position the external power supply and power cord so that it is difficult to pull the power cord out of the power supply.

Ground the Instrument. Before any other connection is made, the instrument must be connected to a protective earth conductor via the three-wire power cable. The power plug shall be inserted only into a grounded outlet. Do not defeat the protective action by using an extension cord without a grounded connector.

 **WARNING**

Any interruption of the protective ground conductor inside or outside the instrument or disconnection of the protective ground terminal is likely to make the instrument dangerous. Intentional interruption is prohibited.

Do Not Operate Without Covers. Do not operate this instrument with covers or panels removed.

Avoid Exposed Circuitry. Do not touch exposed connections and components when power is present.

Do Not Operate With Suspected Failures. If you suspect there is damage to this instrument, have it inspected by qualified service personnel.

Do Not Operate in Wet/Damp Conditions.


Do Not Operate in an Explosive Atmosphere.

Keep Product Surfaces Clean and Dry.

1-5 WEEE and RoHS Status



We, at Huntron are aware of the recycling needs for Waste Electronic and Electrical Equipment (WEEE) and Restriction of certain Hazardous Substances (RoHS) and are co-operating with systems established, worldwide for the collecting and recycling of our products.

 Huntron has applied the Wheeled bin cycle mark (EN50419) to our products. At the present time, most European countries are not complete in their compliance with the European WEEE legislation and they do not have collective systems fully operational and registration initiated. Further recycling information will be added to our website www.huntron.com as it becomes available.

Huntron products, being electronic test equipment, are classified as monitoring and control instruments and are presently exempt from the RoHS directives. Huntron is currently using leaded solder in the construction of our products but we are working for total compliance to RoHS to be completed by July 2006.



Recycling is important to all communities, therefore we ask our customers to be responsible in recycling. Please check your local recycling laws for further information.

SECTION 2

OPERATING INSTRUCTIONS

2-1. INTRODUCTION

This section describes the basic operation of the ProTrack Scanner I. Throughout the rest of this manual the ProTrack Scanner I will be referred to simply as the Scanner I. Take time to read this section carefully so that you can take full advantage of all its capabilities.

2-2. UNPACKING YOUR INSTRUMENT

Your instrument was shipped with the following items:

QTY	DESCRIPTION	HUNTRON P/N
1	Certificate of Compliance	21-1193
2	Clip, 8 pin	07-1235
2	Clip, 16 pin	07-1229
2	Clip, 18 pin	07-1237
2	Clip, 20 pin	07-1234
2	Clip, 24 pin	07-1239
2	Clip, 28 pin	07-1240
2	Clip, 40 pin	07-1230
2	Jumper Assembly 1k Ω	98-0029
2	Jumper Assembly 10k Ω	98-0028
2	Cable Assembly, 20 pin clip	98-0103
2	Cable Assembly, 40 pin clip	98-0102
1	Interface Cable RJ45 24"	98-0173
3	BNC Cable 24" M/M	98-0223
	or	
1	Triple BNC w/ferrites	98-0282
1	Power Cord, USA	98-0015
1	Static Plug Set	98-0256
1	Declaration of Conformity	21-1285
1	CD, Manuals	06-5217

Check the shipment carefully and contact the place of purchase if anything is missing or damaged in shipment. If reshipment is necessary, please use the original shipping carton and packing foam. If these are not available, be sure that adequate protection is provided to prevent damage during shipment.

2-3. PHYSICAL FEATURES

Before you begin to use the Scanner I, please take a few minutes to familiarize yourself with the instrument. All of the externally accessible features are shown in Figure 2-1 and summarized in Table 2-1.




Figure 2-1. External Features

Table 2-1. Controls and Connectors.


Item No.	Item	Description
1	Interface Connector	Connection to the Huntron ProTrack I Model 20.
2	Channel A BNC	Connects to Channel A BNC of the Huntron ProTrack Model 20.
3	Common BNC	Connects to the Common BNC of the Huntron ProTrack Model 20.
4	Channel B BNC	Connects to Channel B BNC of the Huntron ProTrack Model 20.
5	Power Jack	Connects to the external Scanner I Power Supply.
6	Power On	Power Switch with Indicator.
7	Channel A ZIF	40 Pin 0.3 inch to 0.6 inch (7.62mm to 15.24mm) spacing ZIF IC socket.
8	Channel A IDC	64 Pin IDC connector socket.
9	Channel B ZIF	40 Pin 0.3 inch to 0.6 inch (7.62mm to 15.24mm) spacing ZIF IC socket.
10	Channel B IDC	64 Pin IDC connector socket.

**CAUTION - POWER ADAPTER**

Use only the PHIHONG power supply (Model PSA-30U-050) that was included with your Scanner I. Any substitution may damage your instrument and/or result in an unsafe condition.

Refer to the following diagram (see next page) to connect the ProTrack Scanner I to a ProTrack I Model 20.

ProTrack I Model 20/Scanner I/Computer Connections



CABLE HOOKUP USING THE SECONDARY COMPUTER PARALLEL PORT
 PROTRACK I MODEL 20 TO SCANNER I & COMPUTER/PRINTER TO COMPUTER

2-4. SETUP

Note: User should take ESD precautions (wear ground straps) before operating the unit.

The following procedure details how to setup and operate the Scanner I with a ProTrack for in-circuit comparisons of a 16 pin IC on different boards. Although other modes can be used with the Scanner I, this procedure is the one most commonly used for troubleshooting.

1. Connect the Interface cable supplied with your Scanner I to the Scanner connector on the back panel of the ProTrack I. Connect the other end of this cable to the Interface connector located on the back of the Scanner I.
2. Connect a coaxial cable from the Channel A BNC jack on the back panel of the ProTrack to the Channel A jack on the Scanner I. Connect two additional coaxial cables between the ProTrack and Scanner I Common and Channel B jacks.
3. Plug the external Power Supply into the Scanner I Power Jack (if this is not already done). Plug the Power cord into the wall outlet. Turn on the Power Switch on the front panel and the indicator will illuminate.

2-5. TYPICAL APPLICATIONS



CAUTION

The device to be tested must have all power turned off, and have all high voltage capacitors discharged before connecting the Scanner I to the device.

This section shows a typical application of the Scanner I using DIP IC test clips to access components. Using DIP test clips to access a multi-pin component is more convenient than using a single test probe manually to access IC pins one at a time. Follow the general steps below to setup your Scanner I when using DIP clips for testing.




Figure 2-5. Typical Application

1. Connect the two 20 pin DIP clip cables to the two 64 pin IDC sockets on the Scanner I. Attach 16 pin DIP clips to the ends of the cables.
2. Connect the DIP clip end of the left cable to a 16 pin IC on a known-good board. The red stripe end of the clip is pin 1 so be sure that end of the clip is connected to pin 1 of the IC.
3. Connect the DIP clip end of the right cable to the 16 pin IC that is in the same location on the unknown board as the IC on the known-good board (i.e. if you hooked up to U8 or IC9 on one board, hook up to U9 or IC9 on the other board).
4. Connect the Common test lead from the ProTrack I to the same common point on each board. You can also set common pins using the ProTrack I (refer to the ProTrack I manual). In this case you do not need to connect to the common of each board using the common test leads from the ProTrack's common front panel jack. The common is routed through the Scanner I's internal relays and out the 64 pin IDC cables.

The topics that follow clarify various points and expand into other areas.

CIRCUIT SIMILARITY - Devices and circuits being compared should be as nearly identical as possible, otherwise differences may be present which could give misleading signatures. Try to use the same PCB revision level when comparing boards or verify by schematic diagram that the device being examined is wired the same on boards of different revision level.

SELECTING COMMON PINS - In theory any pin on an IC that is not an open circuit could be used for the common pin. In practice, however, the normal procedure is to use one of the power supply pins on an IC as the common pin. V_{SS} , V_{DD} , V_{CC} , and Ground are some typical names for power supply pins. There is one situation where it is sometimes useful to not use a power supply pin. When testing boards where bus architectures are in use, most of the pins on one IC will be connected in parallel with the same pins on other devices. Using the normal procedure above you can see a fault on one bus line, but you do not know which IC is causing it since they are all in parallel. In this event try using one of the “non-bussed” pins on the IC as the common pin. A non-bussed pin is any one that is not connected in parallel with all other ICs. Examples include “Chip Select” and “Enable” lines.

OUT OF CIRCUIT COMPONENTS - When comparing ICs that are not soldered in a board, place the components directly into the ZIF sockets and do not use the DIP clips. Then follow all the other steps of the procedure in the normal manner.

NON-COMPARISON TESTING - When you want to examine the signatures of only one board, connect the appropriate cable to the board.

TESTING CMOS DEVICES - CMOS ICs sometimes produce unstable signatures especially when tested out of circuit in the ZIF sockets of the Scanner I. Whether the device is in-circuit or out of circuit, if instability occurs it is advisable to connect the 10k Ω resistor jumpers provided across the V_{DD} and V_{SS} pins of the device. This will help to reduce or eliminate the unstable signatures. To use the resistor jumpers, select V_{DD} or V_{SS} as the common pin in the normal manner or use common leads.

2-6. EXTERNAL CLEANING



To avoid instrument damage, never get water inside the case or apply solvents to the instrument.

Should the Scanner I case require cleaning, wipe the instrument with a cloth that is lightly dampened with water or mild detergent solution.

2-7. STORAGE INSTRUCTIONS

For optimum protection, store unit indoors in a dry place.

Notes: